

Appl. No. 09/934,870
Amdt. Dated June 19, 2006
Response to Examiner Interview on June 8, 2006

Attorney Docket No. 83357.0001
Customer No.: 26021

Amendments to the Claims:

This listing of claims will replace all prior versions, and listings, of claims in the application:

Listing of Claims:

1. (Currently Amended): An SSB radio communication system comprising:
 - amplitude modulating a carrier wave in a transmitting side by using modulation inputs, wherein the modulation inputs comprise a constant amplitude, sine wave shaped reference pulse signal having a predetermined width and period, and sine wave shaped modulation pulse signals having the same width as the reference pulse signal and amplitudes representing two- or multi-value digital values based on the amplitude of the reference pulse signal,
 - transmitting the amplitude modulated signals on a single side band, and
 - automatically adjusting gains of received signals in a receiving side which are values of peaks of the received signals based on the reference pulse signal, wherein
 - forming the period or frequency of said reference pulse signal in the transmitting side in synchronism with the carrier wave frequency, and
 - determining a local carrier frequency in the receiving side, based on the period or frequency of said reference pulse signal, wherein
 - said reference pulse signal is formed such that the reference pulse signal is provided with a predetermined width and a predetermined period based on said carrier wave frequency of the transmitting circuit.
2. (Cancelled).

Appl. No. 09/934,870

Attorney Docket No. 83357.0001

Amdt. Dated June 19, 2006

Customer No.: 26021

Response to Examiner Interview on June 8, 2006

3. (Previously Presented): A radio apparatus comprising:
a transmitting circuit for single side band communications, and
means for generating modulation inputs, wherein said modulation inputs comprise a constant amplitude, sine wave shaped reference pulse signal having a predetermined width and period, and sine wave shaped modulation pulse signals having the same width as the reference pulse signal and amplitudes representing two- or multi-value digital values based on the amplitude of the reference pulse signal, wherein

said modulation inputs generated by the generating means are supplied to the transmitting circuit so as to amplitude modulate a carrier wave to transmit the amplitude modulated signals through a single side band, wherein

said reference pulse signal is formed such that the reference pulse signal is provided with a predetermined width and a predetermined period based on said carrier wave frequency of the transmitting circuit.

4. (Cancelled).

5. (Currently Amended): A radio apparatus comprising:
an intermediate frequency amplifier for receiving communication signals carried on a single side band, and for automatically controlling the gain of the received signals,
a demodulator for demodulating the received signals based on a local carrier wave frequency, and
gain control means for automatically control the gain of said intermediate frequency amplifier such that a sine wave shaped reference pulse signal, which is contained in the output signals of said intermediate frequency amplifier, and which has a predetermined width and a predetermined period,

Appl. No. 09/934,870
Amdt. Dated June 19, 2006
Response to Examiner Interview on June 8, 2006

Attorney Docket No. 83357.0001
Customer No.: 26021

is peak detected so that its peak value becomes a predetermined value,
wherein

said reference pulse signal which is contained in the output
signals of said intermediate frequency amplifier is peak detected to extract a
row of constant period pulse signals, and wherein said local carrier wave
frequency is adjusted based on said row of constant period pulse signals,
wherein

said reference pulse signal is formed such that the reference pulse
signal is provided with a predetermined width and a predetermined period
based on said carrier wave frequency of the transmitting circuit.

6. (Cancelled).

7. (Previously Presented): A radio apparatus of claim 5, further
comprising a low frequency amplifier disposed in the latter stage of said
demodulator, wherein the gain of said low frequency amplifier is controlled by
the automatic gain control means based on said reference pulse signal
contained in the output signals of said low frequency amplifier.

8. (Original): A radio apparatus for receiving single side band
communication signals modulated by modulation inputs, wherein said
modulation inputs comprise a constant amplitude, sine wave shaped reference
pulse signal, formed based on a carrier frequency, having a predetermined
width and a predetermined period, and sine wave shaped modulation pulse
signals having the same width as the reference pulse signal and amplitudes
representing two- or multi-value digital values based on the amplitude of the
reference pulse signal, the apparatus comprising,

an intermediate frequency amplifier for automatically control the
gain of the modulated signals,

Appl. No. 09/934,870
Amdt. Dated June 19, 2006
Response to Examiner Interview on June 8, 2006

Attorney Docket No. 83357.0001
Customer No.: 26021

a demodulator for demodulating the received signals,
automatic gain control means for peak detecting said reference
pulse signal contained in the output signals of said intermediate frequency
amplifier, and for controlling the gain of said intermediate frequency amplifier
so that its peak value becomes a predetermined value, wherein

the output of said intermediate frequency amplifier is amplitude
detected by a amplitude detector means to extract a frequency component of
the predetermined period of said reference pulse signal, the frequency
obtained based on the frequency obtained by said amplitude detector means is
mixed with the frequency of the output signal of said intermediate frequency
amplifier, and the frequency representing the sum or difference therebetween
is fed to said demodulator as a local carrier frequency wave.

9. (Original): A radio apparatus of claim 8, further comprising a
condenser having a charging/discharging circuit to control the gain of said
intermediate frequency amplifier according to a charging voltage, wherein said
discharging circuit of the condenser is switched on during a period when the
amplitude of said reference pulse signal increases, and switched off during at
least a period of the modulation pulse signal.